

# Steuerungen

## Blanco Two-Light, Ario, Arid


### Blanco Two-Light - swithing unit 24 V DC



Blanco radio control serves warm white/cool white color temperature control purposes for the two-color (Two-Light) lamp systems. The color temperature is simply selected with a rotating knob. The memory function memorizes the last adjusted value. The SET consists of a radio dimmer and radio Receiver.

- Measures radio remote control (lxwxh): 55 mm x 55 mm x 11 mm
- Measures (lxwxh): 178 mm x 57 mm x 21 mm

	finish	power	ampère
76.32549.11	white	36 W	max. 3 A




### Ario - Optodim for angle dimmer 1 - 10 V DC, 12/24 V DC



- Primary: Cable 100 mm with Jo- Jow- or Round LED plug
- secondary: Cable 100 mm - 150 mm with Jo- Jow- or Round LED female
- Measures (lxwxh): 173 mm x 43 mm x 20 mm

	finish	watt	volt	ampère	finish
76.18160.11	white	36 W	12 V	max. 5 A	Jo-connection system
76.18161.11	white	72 W	24 V	max. 5 A	Jow-connection system
76.18162.11	white	120 W	24 V	max. 5 A	Round-connection system




- i** Order the power pack separately (page A-1.38, A-1.25, A-1.17).
- Light controller or dimmer switch order separately "E-No. 548280000 for Optodim 1-10V DC". Electrical installation or connection to be performed by an electrician only.

### Arid - Dalidim for dali contol 12/24 V DC



- Primary: Cable 100 mm with Jo- Jow- or ROUND LED plug
- secondary: Cable 100 mm - 150 mm with Jo- Jow- or ROUND LED female
- Measures (lxwxh): 173 mm x 43 mm x 20 mm

	finish	watt	volt	ampère	finish
76.18163.11	white	36 W	12 V	max. 5 A	Jo-connection
76.18164.11	white	72 W	24 V	max. 5 A	Jow-connection
76.18165.11	white	120 W	24 V	max. 5 A	Round-connection



- i** Order the power pack separately (page A-1.25, A-1.25, A-1.17).
- Light controller or dimmer switch order separately "E-No. 554521000" for Dalidim. Electrical installation or connection to be performed by an electrician only.

**i** Technical information and legend for icons (page A-1.79).

**i** Technical information and legend for icons (page